
# EXITA SERIES



Non-maintained Lead Acid Battery. Universally mounting pattern allows for direct mounting onto conduit boxes. EXITA-Z2172U-N is a great choice for functionality and flexibility in emergency situations.









	DATE	
	PROJECT NAME	
	TYPE	
	QTY	
Z2172U-N	ORDERING CODE	

OPERATING & E	ELECTRICAL
INPUT VOLTAGE	AC120V/277V/347V
INPUT CURRENT	AC120V:0.15A

APPLICATION CONDITION	
AMBIENT TEMPERATURE RANGE	10 to 40°C

COMPATIBLE MOUNTING	
INSTALLATION	Wall Mount

	PERFORMANCE
ССТ	6000-6500K
POWER CONSUMPTION	3.6V/H:0.95-1.15W 12V/H:1.75-2.1W 24V/H:1.95-2.4W

WARRANTY	
SYSTEM WARRANTY - 5 YEARS	

Eralux will warrant defective drivers, LEDs and boards for 5 years from the date of purchase. This warranty is valid only if the fixture is installed and used as per installation guides and specifications. If a defect is present, Eralux will send drivers and boards at no fee with a thorough replacement instructions along with instructions on the return of the defective parts back to Eralux.

MECHANICAL & H	OUSING
HOUSING	Steel Frame
FINISH	White

#### **APPROVALS**


Certification Standards: UL-924


72W at 30mins battery backup time 27W at 90mins battery backup time 22W at 120mins battery backup time




DATE	
PROJECT NAME	
TYPE	
QTY	
ORDERING CODE	Z2172U-N

## **DIMENSIONS** [mm]







#### **ORDERING CODE**

<b>Z2</b>	17	72	U-	N

#### **FIXTURE FAMILY**


Z2172U-N

**ERALUX** emergency LED remote head

#### PHOTOMETRIC DATA

EXITA-Z2172U-N DC24V

## POLAR LUMINOUS INTENSITY GRAPHS



# eralux® **EXITA SERIES**

EMERGENCY LIGHTING EXITA-Z2172U-N

DATE	
PROJECT NAME	
TYPE	
QTY	
ORDERING CODE	Z2172U-N

### **OVERVIEW**



INPUT	AC120V/277V/347V
INPUT CURRENT	AC120V:0.15A
EMERGENCY POWER	22 W
сст	6000K-6500K Suitable for Damp Conditions
Operating Temperature	10 to 40°C
. •	10 to 40°C Steel Frame



Front View



Side View



Top View